

Proprietary Extension for

COMMON-ISDN-API

Version 2.0

**Extension for FAX Paper Formats
and Resolutions**

August 2009

Dialogic Corporation

COPYRIGHT NOTICE AND LEGAL DISCLAIMER

Sixth Edition (August 2009)

206-412-06

Copyright © 2001-2009 Dialogic Corporation. All Rights Reserved. You may not reproduce this document in whole or in part without permission in writing from Dialogic Corporation.

All contents of this document are furnished for informational use only and are subject to change without notice and do not represent a commitment on the part of Dialogic Corporation or its subsidiaries ("Dialogic"). Reasonable effort is made to ensure the accuracy of the information contained in the document. However, Dialogic does not warrant the accuracy of this information and cannot accept responsibility for errors, inaccuracies or omissions that may be contained in this document.

INFORMATION IN THIS DOCUMENT IS PROVIDED IN CONNECTION WITH DIALOGIC® PRODUCTS. NO LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE, TO ANY INTELLECTUAL PROPERTY RIGHTS IS GRANTED BY THIS DOCUMENT. EXCEPT AS PROVIDED IN A SIGNED AGREEMENT BETWEEN YOU AND DIALOGIC, DIALOGIC ASSUMES NO LIABILITY WHATSOEVER, AND DIALOGIC DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY, RELATING TO SALE AND/OR USE OF DIALOGIC PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, MERCHANTABILITY, OR INFRINGEMENT OF ANY INTELLECTUAL PROPERTY RIGHT OF A THIRD PARTY.

Dialogic products are not intended for use in medical, life saving, life sustaining, critical control or safety systems, or in nuclear facility applications.

Due to differing national regulations and approval requirements, certain Dialogic products may be suitable for use only in specific countries, and thus may not function properly in other countries. You are responsible for ensuring that your use of such products occurs only in the countries where such use is suitable. For information on specific products, contact Dialogic Corporation at the address indicated below or on the web at www.dialogic.com.

It is possible that the use or implementation of any one of the concepts, applications, or ideas described in this document, in marketing collateral produced by or on web pages maintained by Dialogic may infringe one or more patents or other intellectual property rights owned by third parties. Dialogic does not provide any intellectual property licenses with the sale of Dialogic products other than a license to use such product in accordance with intellectual property owned or validly licensed by Dialogic and no such licenses are provided except pursuant to a signed agreement with Dialogic. More detailed information about such intellectual property is available from Dialogic's legal department at 9800 Cavendish Blvd., 5th Floor, Montreal, Quebec, Canada H4M 2V9. **Dialogic encourages all users of its products to procure all necessary intellectual property licenses required to implement any concepts or applications and does not condone or encourage any intellectual property infringement and disclaims any responsibility related thereto. These intellectual property licenses may differ from country to country and it is the responsibility of those who develop the concepts or applications to be aware of and comply with different national license requirements.**

Dialogic, Dialogic Pro, Brooktrout, Diva, Cantata, SnowShore, Eicon, Eicon Networks, NMS Communications, NMS (stylized), Eiconcard, SIPcontrol, Diva ISDN, TruFax, Exnet, EXS, SwitchKit, N20, Making Innovation Thrive, Connecting to Growth, Video is the New Voice, Fusion, Vision, PacketMedia, NaturalAccess, NaturalCallControl, NaturalConference, NaturalFax and Shiva, among others as well as related logos, are either registered trademarks or trademarks of Dialogic Corporation or its subsidiaries. Dialogic's trademarks may be used publicly only with permission from Dialogic. Such permission may only be granted by Dialogic's legal department at 9800 Cavendish Blvd., 5th Floor, Montreal, Quebec, Canada H4M 2V9. Any authorized use of Dialogic's trademarks will be subject to full respect of the trademark guidelines published by Dialogic from time to time and any use of Dialogic's trademarks requires proper acknowledgement.

The names of actual companies and products mentioned herein are the trademarks of their respective owners.

Motivation:

The current **COMMON-ISDN-API** specification defines paper formats ISO A4, ISO B4 and ISO A3 at standard resolution (R8 x 3.85) and high resolution (R8 x 7.7). Support for B4 and A3 is even optional.

The following document proposes a **COMMON-ISDN-API** extension that enables FAX document transmission and reception with paper formats ISO A4, ISO B4 and ISO A3 and these resolutions as specified in T.30:

- R8 x 3.85
- R8 x 7.7
- R8 x 15.4
- R16 x 15.4
- 200 x 200
- 300 x 300
- 400 x 400

The page format and resolution information is passed via appropriate fields in the SFF page header.

To minimize the additions required in a CAPI application in order to make use of the extension, the new functionality is added directly to the existing SFF format. This means that there is a risk to conflict with future official extensions of the **COMMON-ISDN-API**. To make sure that this will not result in incompatibilities, support for FAX paper formats and resolutions has to be enabled explicitly. It is guaranteed that any future CAPI extension that would cause incompatibility is turned off then.

It has to be enabled by the application for a designated controller through a manufacturer request command 9 (Options request) with bit 6 (Enable FAX paper formats and resolutions) set. It will stay active until either the application releases the **COMMON-ISDN-API** or issues another options request with bit 6 not set.

An application can determine whether the **COMMON-ISDN-API** supports FAX paper formats and resolutions by examining the CAPI profile and searching the manufacturer string for "Eicon" or by examining the CAPI profile and trying the manufacturer command 9 described below.

Changes since the first version from 12.1.2001:

- Added support for resolutions 300 x 600, 400 x 800, 600 x 1200, 600 x 600 and 1200 x 1200 dpi.

4.2.2.7 CAPI_GET_PROFILE

Applications call CAPI_GET_PROFILE to retrieve capability information from **COMMON-ISDN-API**. **COMMON-ISDN-API** copies information about implemented features, the total number of controllers and protocols supported by the requested controller to a 64-byte buffer passed by the calling application. The application must ignore unknown bits. **COMMON-ISDN-API** sets every reserved field to zero. CAPI_GET_PROFILE fills the buffer with the following structure:

Type	Description
2 bytes	number of installed controllers, least significant byte first
2 bytes	number of supported B-channels, least significant byte first
4 bytes	Global Options (bit field): [0]: internal controller supported [1]: external equipment supported [2]: Handset supported (external equipment must also be set) [3]: DTMF supported [4]: Supplementary Services (see Part III) [5]: channel allocation supported (leased lines) [6]: parameter <i>B channel operation</i> supported [7]: Line Interconnect supported [8]...[31]: reserved
4 bytes	B1 protocol support (bit field): [0]: 64 kbit/s with HDLC framing, always set. [1]: 64 kbit/s bit-transparent operation with byte framing from the network [2]: V.110 asynchronous operation with start/stop byte framing [3]: V.110 synchronous operation with HDLC framing [4]: T.30 modem for fax group 3 [5]: 64 kbit/s inverted with HDLC framing. [6]: 56 kbit/s bit-transparent operation with byte framing from the network [7]: Modem with all negotiations [8]: Modem asynchronous operation with start/stop byte framing [9]: Modem synchronous operation with HDLC framing [10]...[31]: reserved
4 bytes	B2 protocol support (bit field): [0]: ISO 7776 (X.75 SLP), always set [1]: Transparent [2]: SDLC [3]: LAPD in accordance with Q.921 for D-channel X.25 (SAPI 16) [4]: T.30 for fax group 3 [5]: Point-to-Point Protocol (PPP) [6]: Transparent (ignoring framing errors of B1 protocol) [7]: Modem error correction and compression (V.42 bis or MNP5) [8]: ISO 7776 (X.75 SLP) modified supporting V.42 bis compression [9]: V.120 asynchronous mode [10]: V.120 asynchronous mode supporting V.42 bis [11]: V.120 bit-transparent mode [12]: LAPD in accordance with Q.921 including free SAPI selection [13]...[31]: reserved

4 bytes	B3 protocol support (bit field): [0]: Transparent, always set [1]: T.90NL with compatibility to T.70NL in accordance to T.90 Appendix II. [2]: ISO 8208 (X.25 DTE-DTE) [3]: X.25 DCE [4]: T.30 for fax group 3 [5]: T.30 for fax group 3 with extensions [6]: reserved [7]: Modem [8]...[31]: reserved
24 bytes	reserved for COMMON-ISDN-API use
4 bytes	Private options (bit field): [0]...[5]: reserved [6]: FAX paper formats and resolutions [7]...[31]: reserved
16 bytes	Manufacturer-specific information

CAPI_GET_PROFILE information structure

Manu ID (dword)

The purpose of the parameter *Manu ID* is to communicate a dword, which identifies the manufacturer in MANUFACTURER messages. Every manufacturer supplying MANUFACTURER messages should choose a unique value (such as an abbreviation of the company name).

The manufacturer ID used by Dialogic is:

0x44444944

This information element appears in:

**MANUFACTURER_REQ
MANUFACTURER_RESP
MANUFACTURER_CONF
MANUFACTURER_IND**

Manufacturer Specific

The purpose of the parameter *manufacturer specific* is to exchange manufacturer-specific information.

Manufacturer specific information for MANUFACTURER_REQ:

word	manufacturer command	Manufacturer specific operation requested.
struct	manufacturer command parameters	Command dependent parameters for manufacturer request.

Manufacturer specific information for MANUFACTURER_CONF:

word	manufacturer command	Manufacturer specific operation that was requested.
word	info	Result of the operation according to COMMON-ISDN-API definition of Info.

This information element appears in:

**MANUFACTURER_REQ
MANUFACTURER_RESP
MANUFACTURER_CONF
MANUFACTURER_IND**

Manufacturer Command

The purpose of the parameter *manufacturer command* is to specify the kind of operation requested in a MANUFACTURER_REQ.

The following manufacturer commands are defined:

- 1: Assign PLCI
- 2: Advanced Codec control
- 3: DSP control
- 4: Signaling control
- 5: RXT control
- 6: IDI control
- 7: Configuration control
- 8: Remove Codec
- 9: Options request

This information element appears in:

Manufacturer Specific

Manufacturer Command Parameters

The purpose of the parameter *manufacturer command parameters* is to specify command dependent parameters.

Parameters for manufacturer command 9: Options Request:

dword	Options mask	Manufacturer specific options that have to be enabled: [Bit 0..5]: reserved, must be set to 0 [Bit 6]: Enable FAX paper formats and resolutions [Bit 7..31]: reserved, must be set to 0
-------	--------------	--

Note: The *Options mask* may be set independently for a controller and for a PLCI. Options apply if they are either set for the controller or for the PLCI.

This information element appears in:

Manufacturer Command

ANNEX B (NORMATIVE): SFF FORMAT

B.1 Introduction

SFF (Structured Fax File) is a representation especially for fax group 3 documents. It consists of information concerning the page structure and compressed line data of the fax document. An SFF-formatted document always starts with a header, which is valid for the complete document. Every page starts with a page header. This is followed by the pixel information, line by line. As the SFF format is a file format specification, some entries in header structures (e.g. double-chaining of pages) may not be used or supported by **COMMON-ISDN-API**.




Figure 6: SFF format

B.2 SFF coding rules

The following type conventions are used:

byte	8-bit unsigned
word	16-bit unsigned integer, least significant octet first
dword	32-bit unsigned integer, least significant word first

B.2.1 Document header

Parameter	Type	Comment
SFF_Id	dword	Magic value (identification) of SFF Format: coded as 0x66666653 ("SFFF")
Version	byte	Version number of SFF document: coded 0x01
reserved	byte	Reserved for future extensions; coded 0x00
User Information	word	Manufacturer-specific user information (not used by COMMON-ISDN-API , coded as 0x0000)
Page Count	word	Number of pages in the document. Must be coded 0x0000 if not known (as in the case of receiving a document).
OffsetFirstPageHeader	word	Byte offset of first page header from start of document header. This value is normally equal to the size of the document header (0x14), but there could be additional user-specific data between the document header and the first page header. COMMON-ISDN-API ignores and does not provide such additional data.
OffsetLastPageHeader	dword	Byte offset of last page header from start of document header. Must be coded 0x00000000 if not known (as in the case of receiving a document).
OffsetDocumentEnd	dword	Byte offset of document end from start of document header. Must be coded 0x00000000 if not known (as in the case of receiving a document).

B.2.2 Page header

Parameter	Type	Comment
PageHeaderID	byte	254 (Page data record type)
PageHeaderLen	byte	0 : Document end 1...255 : byte offset of first page data from the <i>Resolution Vertical</i> field of the page header. This value is normally equal to the size of the remainder of the header (0x10), but there could be additional user-specific data between page header and page data. COMMON-ISDN-API ignores and not provide such additional data.
Resolution Vertical	byte	Definition of vertical resolution; different resolutions in one document may be ignored by COMMON-ISDN-API 0 : 98 lpi (standard) 1 :: 196 lpi (high resolution) 2...254 : reserved 255 : end of document (should not be used: <i>PageHeaderLen</i> should be coded 0 instead) If FAX paper formats and resolutions is enabled 0x00 : 98 lpi (3.85 lines per millimeter) 0x01 : 196 lpi (7.7 lines per millimeter) 0x02..0x7f : reserved 0x80 : reserved 0x81 : 100 lpi 0x82 : reserved 0x83 : 200 lpi 0x84 : reserved 0x85 : 300 lpi 0x86 : 392 lpi (15.4 lines per millimeter) 0x87 : 400 lpi 0x88..0x8a : reserved 0x8b : 600 lpi 0x8c..0x8e : reserved 0x8f : 800 lpi 0x90..0x96 : reserved 0x97 : 1200 lpi 0x98..0xff : reserved
Resolution Horizontal	byte	Definition of horizontal resolution 0 : 203 dpi (standard) 1...255 : reserved If FAX paper formats and resolutions is enabled 0x00 : 203 dpi (R8, 8 pels per millimeter) 0x01..0x7f : reserved 0x80 : reserved 0x81 : reserved 0x82 : reserved 0x83 : 200 dpi 0x84 : reserved 0x85 : 300 dpi 0x86 : 406 dpi (R16, 16 pels per millimeter) 0x87 : 400 dpi 0x88..0x8a : reserved 0x8b : 600 dpi 0x8c..0x96 : reserved 0x97 : 1200 dpi 0x98..0xff : reserved
Coding	byte	Definition of pixel line coding 0 : modified Huffman coding 1...255 : reserved
reserved	byte	Coded as 0

Line Length	word	Number of pixels per line 1728: standard fax G3 2048: B4 (optional) 2432: A3 (optional) Support for additional values is optional for COMMON-IS-DN-API If FAX paper formats and resolutions is enabled 1728: ISO A4 at R8 x 3.85, R8 x 7.7, R8 x 15.4, 200 x 200 2048: ISO B4 at R8 x 3.85, R8 x 7.7, R8 x 15.4, 200 x 200 2432: ISO A3 at R8 x 3.85, R8 x 7.7, R8 x 15.4, 200 x 200 2592: ISO A4 at 300 x 300, 300 x 600 3072: ISO B4 at 300 x 300, 300 x 600 3648: ISO A3 at 300 x 300, 300 x 600 3456: ISO A4 at R16 x 15.4, 400 x 400, 400 x 800 4096: ISO B4 at R16 x 15.4, 400 x 400, 400 x 800 4864: ISO A3 at R16 x 15.4, 400 x 400, 400 x 800 5184: ISO A4 at 600 x 600, 600 x 1200 6144: ISO B4 at 600 x 600, 600 x 1200 7296: ISO A3 at 600 x 600, 600 x 1200 10368: ISO A4 at 1200 x 1200 12288: ISO B4 at 1200 x 1200 14592: ISO A3 at 1200 x 1200
Page Length	word	Number of pixel lines per page. If not known, coded as 0x0000 .
OffsetPreviousPage	dword	Byte offset to previous page header or 0x00000000 . Coded as 0x00000001 if first page.
OffsetNextPage	dword	Byte offset to next page header or 0x00000000 . Coded as 0x00000001 if last page.

B.2.3 Page data

Page data are coded line by line: data describe each pixel row. Lines are coded as records of variable length; each line is coded according to the element *coding* in the page header. At present, only modified Huffman coding is supported. MH coding is bit-oriented: the pixel bits are stored in the bits of code words least significant first. No EOL code words or fill bits are included. If the data include EOL code words, **COMMON-ISDN-API** ignores these.

Each record is identified by the first byte:

- **1...216:** a pixel row with 1...216 MH-coded bytes follows immediately
- **0:** escape code for a pixel row with more than 216 MH-coded bytes. In this case, the following word in the range **218...32767** defines the number of MH-coded bytes which follow.
- **217...253:** white space, skip 1...37 empty lines
- **254:** start of page header (see above)
- **255:** if followed by a byte with value **0**, illegal line coding. Applications may choose whether to interpret this line as empty or as a copy of the previous line. If this byte is followed by a byte with a value **1...255**, then 1...255 bytes of additional user information follow (reserved for future extensions).